

## KSE13008/13009

## **High Voltage Switch Mode Application**

- High Speed Switching
- Suitable for Switching Regulator and Motor Control



1.Base 2.Collector 3.Emitter

### **NPN Silicon Transisor**

## Absolute Maximum Ratings T<sub>C</sub>=25°C unless otherwise noted

Symbol	Parameter	Value	Units	
V <sub>CBO</sub>	Collector-Base Voltage			
	: KSE13008	600	V	
	: KSE13009	700	V	
V <sub>CEO</sub>	Collector-Emitter Voltage			
	: KSE13008	300	V	
	: KSE13009	400	V	
V <sub>EBO</sub>	Emitter-Base Voltage	9	V	
I <sub>C</sub>	Collector Current (DC)	12	А	
I <sub>CP</sub>	Collector Current (Pulse)	24	А	
I <sub>B</sub>	Base Current	6	А	
P <sub>C</sub>	Collector Dissipation (T <sub>C</sub> =25°C)	100	W	
TJ	Junction Temperature	150	°C	
T <sub>STG</sub>	Storage Temperature	- 65 ~ 150	°C	

### Electrical Characteristics T<sub>C</sub>=25°C unless otherwise noted

Symbol	Parameter	Test Condition	Min.	Тур.	Max.	Units
V <sub>CEO</sub> (sus)	Collector-Emitter Sustaining Voltage : KSE13008 : KSE13009	I <sub>C</sub> = 10mA, I <sub>B</sub> = 0	300 400			V V
I <sub>EBO</sub>	Emitter Cut-off Current	$V_{EB} = 9V, I_{C} = 0$			1	mA
h <sub>FE</sub>	* DC Current Gain	$V_{CE} = 5V, I_{C} = 5A$ $V_{CE} = 5V, I_{C} = 8A$	8 6		40 30	
V <sub>CE</sub> (sat)	* Collector-Emitter Saturation Voltage	$I_C = 5A, I_B = 1A$ $I_C = 8A, I_B = 1.6A$ $I_C = 12A, I_B = 3A$			1 1.5 3	V V V
V <sub>BE</sub> (sat)	* Base-Emitter Saturation Voltage	$I_C = 5A, I_B = 1A$ $I_C = 8A, I_B = 1.6A$			1.2 1.6	V V
C <sub>ob</sub>	Output Capacitance	V <sub>CB</sub> = 10V, f = 0.1MHz		180		pF
f <sub>T</sub>	Current Gain Bandwidth Product	$V_{CE} = 10V, I_{C} = 0.5A$	4			MHz
t <sub>ON</sub>	Turn On Time	$V_{CC} = 125V, I_{C} = 8A$			1.1	μs
t <sub>STG</sub>	Storage Time	$I_{B1} = -I_{B2} = 1.6A$			3	μs
t <sub>F</sub>	Fall Time	$R_L = 15,6\Omega$			0.7	μs

<sup>\*</sup> Pulse test: PW≤300μs, Duty cycle≤2%

## **Typical Characteristics**




Figure 1. DC current Gain




Figure 2. Base-Emitter Saturation Voltage Collector-Emitter Saturation Voltage




Figure 3. Collector Output Capacitance




Figure 4. Turn On Time




Figure 5. Turn Off Time




Figure 6. Safe Operating Area

©2001 Fairchild Semiconductor Corporation

# Typical Characteristics (Continued)






Figure 7. DC current Gain

## **Package Demensions**

TO-220





Dimensions in Millimeters

#### **TRADEMARKS**

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx™	FAST <sup>®</sup>	OPTOPLANAR™	SuperSOT™-3
Bottomless™	FASTr™	PACMAN™	SuperSOT™-6
CoolFET™	FRFET™	$POP^{TM}$	SuperSOT™-8
CROSSVOLT™	GlobalOptoisolator™	PowerTrench <sup>®</sup>	SyncFET™
DenseTrench™	GTO™	QFET™	TinyLogic™
DOME™	HiSeC™	QS™	UHC™
EcoSPARK™	ISOPLANAR™	QT Optoelectronics™	UltraFET <sup>®</sup>
E <sup>2</sup> CMOS <sup>™</sup>	LittleFET™	Quiet Series™	VCX™
EnSigna™	MicroFET™	SLIENT SWITCHER®	
FACT™	MICROWIRE™	SMART START™	
FACT Quiet Series™	OPTOLOGIC™	Stealth™	

### **DISCLAIMER**

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:


- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
- 2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.


### PRODUCT STATUS DEFINITIONS

#### **Definition of Terms**

Datasheet Identification	Product Status	Definition		
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.		
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.		
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.		
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.		

©2001 Fairchild Semiconductor Corporation Rev. H2





Product	Product status	Pricing*	Package type	Leads	Packing method
KSE13009H2	Full Production	\$0.81	TO-220	3	BULK
KSE13009H2TU	Full Production	\$0.81	TO-220	3	RAIL
KSE13009	Full Production	\$0.81	TO-220	3	BULK
KSE13009TU	Full Production	\$0.81	TO-220	3	RAIL

<sup>\* 1,000</sup> piece Budgetary Pricing

### back to top

٠

my Fairchild company

<u>Home</u> | <u>Find products</u> | <u>Technical information</u> | <u>Buy products</u> | <u>Support</u> | <u>Company</u> | <u>Contact us</u> | <u>Site index</u> | <u>Privacy policy</u>

© Copyright 2002 Fairchild Semiconductor