

PART NUMBER

LM307J-ROCV

Rochester Electronics Manufactured Components

Rochester branded components are manufactured using either die/wafers purchased from the original suppliers or Rochester wafers recreated from the original IP. All re-creations are done with the approval of the Original Component Manufacturer. (OCM)

Parts are tested using original factory test programs or Rochester developed test solutions to guarantee product meets or exceeds the OCM data sheet.

Quality Overview

- ISO-9001
- AS9120 certification
- Qualified Manufacturers List (QML) MIL-PRF-38535
 - Class Q Military
 - Class V Space Level

Qualified Suppliers List of Distributors (QSLD)

• Rochester is a critical supplier to DLA and meets all industry and DLA standards.

Rochester Electronics, LLC is committed to supplying products that satisfy customer expectations for quality and are equal to those originally supplied by industry manufacturers.

The original manufacturer's datasheet accompanying this document reflects the performance and specifications of the Rochester manufactured version of this device. Rochester Electronics guarantees the performance of its semiconductor products to the original OCM specifications. 'Typical' values are for reference purposes only. Certain minimum or maximum ratings may be based on product characterization, design, simulation, or sample testing.

LM107,LM207,LM307

LM107 LM207 LM307 Operational Amplifiers



Literature Number: SNOSBS4A

National Semiconductor

December 1994

_M107/LM207/LM307 Operational Amplifiers

LM107/LM207/LM307 Operational Amplifiers

General Description

The LM107 series are complete, general purpose operational amplifiers, with the necessary frequency compensation built into the chip. Advanced processing techniques make the input currents a factor of ten lower than industry standards like the 709. Yet, they are a direct, plug-in replacement for the 709, LM101A and 741.

The LM107 series offers the features of the LM101A, which makes its application nearly foolproof. In addition, the device provides better accuracy and lower noise in high impedance circuitry. The low input currents also make it particularly well suited for long integrators or timers, sample and hold circuits and low frequency waveform genera-

tors. Further, replacing circuits where matched transistor pairs buffer the inputs of conventional IC op amps, it can give lower offset voltage and drift at a lower cost.

The LM107 is guaranteed over a -55°C to $+125^\circ\text{C}$ temperature range, the LM207 from -25°C to $+85^\circ\text{C}$ and the LM307 from 0°C to $+70^\circ\text{C}.$

- Features
- Offset voltage 3 mV maximum over temperature
- Input current 100 nA maximum over temperature
- Offset current 20 nA maximum over temperature
- Guaranteed drift characteristics



© 1995 National Semiconductor Corporation TL/H/7757

RRD-B30M115/Printed in U. S. A.

Absolute Maximum Ratings If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/ Distributors for availability and specifications. (Note 4) LM107/LM207 LM307 Supply Voltage $\pm 18V$ $\pm 22V$ T_{MIN} Тмах Power Dissipation (Note 1) 500 mW 500 mW Differential Input Voltage $\pm 30V$ $\pm 30V$ LM107 −55°C +125°C Input Voltage (Note 2) $\pm\,15V$ $\pm\,15V$ LM207 -25°C +85°C Output Short Circuit Duration Continuous Continuous LM307 0°C +70°C Operating Temperature Range (T_A) ESD rating to be determined. (LM107) -55°C to +125°C $0^{\circ}C$ to $+70^{\circ}C$ (LM207) -25°C to +85°C Storage Temperature Range $-65^{\circ}C$ to $+150^{\circ}C$ $-65^{\circ}C$ to $+150^{\circ}C$ 260°C 260°C Lead Temperature (Soldering, 10 sec) **Electrical Characteristics** (Note 3) LM107/LM207 LM307 Parameter Conditions Units Min Тур Max Min Тур Max Input Offset Voltage $T_A = 25^{\circ}C, R_S \le 50 \text{ k}\Omega$ 0.7 2.0 2.0 7.5 m٧ Input Offset Current $T_A = 25^{\circ}C$ 3.0 50 1.5 10 nA $T_A = 25^{\circ}C$ Input Bias Current 30 75 70 250 nA $T_A = 25^{\circ}C$ Input Resistance 1.5 4.0 0.5 2.0 MΩ $T_A = 25^{\circ}C$ Supply Current $V_{S} = \pm 20V$ 1.8 3.0 mΑ $V_{S} = \pm 15V$ 1.8 3.0 mΑ $T_{A} = 25^{\circ}C, V_{S} = \pm 15V$ Large Signal Voltage 50 160 25 160 V/mV Gain $V_{OUT}=~\pm\,10V,\,R_L\geq 2\,k\Omega$ $R_S \leq 50 \ k\Omega$ Input Offset Voltage 3.0 10 mV Average Temperature μV/°C 3.0 Coefficient of Input 15 6.0 30 Offset Voltage Input Offset Current 20 70 nA $25^{\circ}C \leq T_{A} \leq T_{MAX}$ Average Temperature 0.01 0.1 0.01 0.3 nA/°C Coefficient of Input $T_{MIN} \leq T_A \leq 25^\circ C$ 0.02 0.2 0.02 0.6 nA/°C Offset Current Input Bias Current 100 300 nA Supply Current $T_{A}=\,+\,125^{\circ}C,\,V_{S}=\,\pm\,20V$ 1.2 2.5 mΑ

Parameter	Conditions	LM107/LM207			LM307			Units
T arameter		Min	Тур	Max	Min	Тур	Max	0.1113
Large Signal Voltage Gain	$\label{eq:VS} \begin{split} V_S = ~\pm~15V, V_{OUT} = ~\pm~10V \\ R_L \geq 2~k\Omega \end{split}$	25			15			V/mV
Output Voltage Swing	$V_{S} = \pm 15V$ $R_{L} = 10 k\Omega$ $R_{L} = 2 k\Omega$	±12 ±10	±14 ±13		±12 ±10	±14 ±13		V V
Input Voltage Range	$V_{S} = \pm 20V \\ V_{S} = \pm 15V$	±15	+ 15 - 13		±12	+ 15 - 13		V V
Common Mode Rejection Ratio	${\sf R}_S \le 50 \ \text{k}\Omega$	80	96		70	90		dB
Supply Voltage Rejection Ratio	${\sf R}_{S} \le 50 \ {\sf k}\Omega$	80	96		70	96		dB

Note 1: The maximum junction temperature of the LM107 is 150°C, and the LM207/LM307 is 100°C. For operating at elevated temperatures, devices in the H08 package must be derated based on a thermal resistance of 165°C/W, junction to ambient, or 30°C/W, junction to case. The thermal resistance of the dual-in-line package is 100°C/W, junction to ambient.

Note 2: For supply voltages less than \pm 15V, the absolute maximum input voltage is equal to the supply voltage.

Note 3: These specifications apply for $\pm 5V \le V_S \le \pm 20V$ and $-55^{\circ}C \le T_A \le \pm 125^{\circ}C$ for the LM107 or $-25^{\circ}C \le T_A + 85^{\circ}C$ for the LM207, and $0^{\circ}C \le T_A \le \pm 70^{\circ}C$ and $\pm 5V \le V_S \le \pm 15V$ for the LM307 unless otherwise specified.

Note 4: Refer to RETS107X for LM107H and LM107J military specifications.

Schematic Diagram*

















National does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry and specifications.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		Applications	
Audio	www.ti.com/audio	Communications and Telecom	www.ti.com/communications
Amplifiers	amplifier.ti.com	Computers and Peripherals	www.ti.com/computers
Data Converters	dataconverter.ti.com	Consumer Electronics	www.ti.com/consumer-apps
DLP® Products	www.dlp.com	Energy and Lighting	www.ti.com/energy
DSP	dsp.ti.com	Industrial	www.ti.com/industrial
Clocks and Timers	www.ti.com/clocks	Medical	www.ti.com/medical
Interface	interface.ti.com	Security	www.ti.com/security
Logic	logic.ti.com	Space, Avionics and Defense	www.ti.com/space-avionics-defense
Power Mgmt	power.ti.com	Transportation and Automotive	www.ti.com/automotive
Microcontrollers	microcontroller.ti.com	Video and Imaging	www.ti.com/video
RFID	www.ti-rfid.com		
OMAP Mobile Processors	www.ti.com/omap		
Wireless Connectivity	www.ti.com/wirelessconnectivity		

TI E2E Community Home Page

e2e.ti.com

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2011, Texas Instruments Incorporated