

# FDP7045L/FDB7045L

# N-Channel Logic Level PowerTrench<sup>O</sup> MOSFET


### **General Description**


This N-Channel Logic Level MOSFET has been designed specifically to improve the overall efficiency of DC/DC converters using either synchronous or conventional switching PWM controllers.


These MOSFETs feature faster switching and lower gate charge than other MOSFETs with comparable  $R_{\text{DS(ON)}}$  specifications resulting in DC/DC power supply designs with higher overall efficiency.

### **Features**

- 100 A, 30 V  $R_{DS(ON)} = 4.5 \text{ m}\Omega$  @  $V_{GS} = 10 \text{ V}$   $R_{DS(ON)} = 6.0 \text{ m}\Omega$  @  $V_{GS} = 4.5 \text{ V}$
- Critical DC electrical parameters specified at elevated temperature
- High performance trench technology for extremely low  $R_{\mbox{\scriptsize DS}(\mbox{\scriptsize ON})}$
- 175°C maximum junction temperature rating







Absolute Maximum Ratings T<sub>A</sub>=25°C unless otherwise noted

Symbol	Parameter		Ratings	Units
V <sub>DSS</sub>	Drain-Source Voltage		30	V
V <sub>GSS</sub>	Gate-Source Voltage		± 20	V
I <sub>D</sub>	Drain Current - Continuous	(Note 1)	100	А
			75	
	- Pulsed	(Note 1)	300	
P <sub>D</sub>	Total Power Dissipation @ T <sub>C</sub> = 25°C		107	W
	Derate above 25°C		0.7	W/°C
T <sub>J</sub> , T <sub>STG</sub>	Operating and Storage Junction Temperature Range		-55 to +175	°C

**FDB Series** 

### **Thermal Characteristics**

$R_{\theta JC}$	Thermal Resistance, Junction-to-Case	1.4	°C/W
$R_{\theta JA}$	Thermal Resistance, Junction-to-Ambient	62.5	°C/W

**Package Marking and Ordering Information** 

Device Marking	Device	Reel Size	Tape width	Quantity
FDB7045L	FDB7045L	13"	24mm	800 units
FDP7045L	FDP7045L	Tube	n/a	45

Symbol	Parameter	Test Conditions	Min	Тур	Max	Units
Drain-So	ource Avalanche Ratings (Note	e 1)	ı			
W <sub>DSS</sub>	Single Pulse Drain-Source Avalanche Energy	$V_{DD} = 15 \text{ V}, \qquad I_D = 75 \text{ A}$			330	mJ
I <sub>AR</sub>	Maximum Drain-Source Avalanche Current				75	Α
Off Char	acteristics	1				
BV <sub>DSS</sub>	Drain-Source Breakdown Voltage	$V_{GS} = 0 \text{ V}, \qquad I_{D} = 250 \mu\text{A}$	30			V
ΔBV <sub>DSS</sub> ΔT <sub>J</sub>	Breakdown Voltage Temperature Coefficient	$I_D = 250 \mu A$ , Referenced to 25°C		25		mV/°C
I <sub>DSS</sub>	Zero Gate Voltage Drain Current	$V_{DS} = 24 \text{ V}, \qquad V_{GS} = 0 \text{ V}$			1	μΑ
I <sub>GSS</sub>	Gate-Body Leakage	$V_{GS} = \pm 20 \text{ V},  V_{DS} = 0 \text{ V}$			± 100	nA
On Char	acteristics (Note 2)					
V <sub>GS(th)</sub>	Gate Threshold Voltage	$V_{DS} = V_{GS}, I_{D} = 250 \mu A$	1	1.8	3	V
$\Delta V_{GS(th)} \over \Delta T_J$	Gate Threshold Voltage Temperature Coefficient	$I_D$ = 250 $\mu$ A, Referenced to 25°C		-6		mV/°C
R <sub>DS(on)</sub>	Static Drain–Source On– Resistance	$V_{GS} = 10 \text{ V},  I_D = 50 \text{ A}$ $V_{GS} = 4.5 \text{ V},  I_D = 40 \text{ A}$ $V_{GS} = 10 \text{ V}, I_D = 50 \text{ A}, T_J = 125^{\circ}\text{C}$		3.5 4.0 5.5	4.5 6.0 7.0	mΩ
I <sub>D(on)</sub>	On–State Drain Current	$V_{GS} = 10 \text{ V}, \qquad V_{DS} = 10 \text{ V}$	50			Α
<b>g</b> FS	Forward Transconductance	$V_{DS} = 5V$ , $I_{D} = 50 \text{ A}$		165		S
Dynamic	Characteristics		•			
C <sub>iss</sub>	Input Capacitance	$V_{DS} = 15 \text{ V}, \qquad V_{GS} = 0 \text{ V},$		4357		pF
Coss	Output Capacitance	f = 1.0 MHz		1092		pF
C <sub>rss</sub>	Reverse Transfer Capacitance			399		pF
R <sub>G</sub>	Gate Resistance	V <sub>GS</sub> = 15 mV, f = 1.0 MHz		1.4		Ω
Switchin	g Characteristics (Note 2)					
t <sub>d(on)</sub>	Turn-On Delay Time	$V_{DD} = 15V$ , $I_D = 1 A$ ,		16	29	ns
t <sub>r</sub>	Turn-On Rise Time	$V_{GS} = 10 \text{ V}, \qquad R_{GEN} = 6 \Omega$		13	24	ns
t <sub>d(off)</sub>	Turn-Off Delay Time			74	119	ns
t <sub>f</sub>	Turn-Off Fall Time			41	66	ns
Q <sub>g</sub>	Total Gate Charge	$V_{DS} = 15 \text{ V}, \qquad I_{D} = 50 \text{ A},$		41	58	nC
Q <sub>gs</sub>	Gate-Source Charge	$V_{GS} = 5 V$		12		nC
$Q_{gd}$	Gate-Drain Charge			14		nC
Drain-So	ource Diode Characteristics	and Maximum Ratings				
Is	Maximum Continuous Drain-Source				75	Α
V <sub>SD</sub>	Drain–Source Diode Forward Voltage	$V_{GS} = 0 \text{ V},  I_{S} = 50 \text{ A}$ (Note 1)		0.91	1.2	V
t <sub>rr</sub>	Diode Reverse Recovery Time	I <sub>F</sub> = 50 A,		48		nS
Q <sub>rr</sub>	Diode Reverse Recovery Charge	$d_{iF}/d_{t} = 100 \text{ A/}\mu\text{s}$		42		nC

#### Notes:

- 1. Calculated continuous current based on maximum allowable junction temperature. Actual maximum continuous current limited by package constraints to 75A.
- 2. Pulse Test: Pulse Width < 300μs, Duty Cycle < 2.0%

# **Typical Characteristics**




Figure 1. On-Region Characteristics.




Figure 3. On-Resistance Variation with Temperature.




Figure 5. Transfer Characteristics.




Figure 2. On-Resistance Variation with Drain Current and Gate Voltage.




Figure 4. On-Resistance Variation with Gate-to-Source Voltage.





Figure 6. Body Diode Forward Voltage Variation with Source Current and Temperature.

# **Typical Characteristics**







Figure 7. Gate Charge Characteristics.








Figure 9. Maximum Safe Operating Area.

Figure 10. Single Pulse Maximum Power Dissipation.




Figure 11. Transient Thermal Response Curve.

### **TRADEMARKS**

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

$ACEx^{TM}$	FACT Quiet Series™	ImpliedDisconnect™	PACMAN™	SPM™
ActiveArray™	FAST®	ISOPLANAR™	$POP^{TM}$	Stealth™
Bottomless™	FASTr™	LittleFET™	Power247™	SuperFET™
CoolFET™	FPS™	$MICROCOUPLER^{TM}$	PowerSaver™	SuperSOT™-3
CROSSVOLT™	FRFET™	MicroFET™	PowerTrench®	SuperSOT™-6
DOME™	GlobalOptoisolator™	MicroPak™	QFET®	SuperSOT™-8
EcoSPARK™	GTO™ .	MICROWIRE™	$QS^{TM}$	SyncFET™
E <sup>2</sup> CMOS <sup>TM</sup>	HiSeC™	MSX <sup>TM</sup>	QT Optoelectronics™	TinyLogic <sup>®</sup>
EnSigna™	I <sup>2</sup> C <sup>TM</sup>	MSXPro™	Quiet Series™	TINYOPTO™
FACT™	i-Lo™	$OCX^{TM}$	RapidConfigure™	TruTranslation™
Across the boar	d. Around the world.™	OCXPro™	RapidConnect™	UHC™
The Power Fran		OPTOLOGIC®	SILENT SWITCHER®	UltraFET®
Programmable A		OPTOPLANAR™	SMART START™	VCX™

### **DISCLAIMER**

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the
- 2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

### PRODUCT STATUS DEFINITIONS

#### **Definition of Terms**

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.