SCBS020A - SEPTEMBER 1988 - REVISED NOVEMBER 1993

- State-of-the-Art BiCMOS Design Significantly Reduces I_{CCZ}
- ESD Protection Exceeds 2000 V Per MIL-STD-883C, Method 3015
- Package Options Include Plastic Small-Outline (DW) Packages, Ceramic Chip Carriers (FK) and Flatpacks (W), and Plastic and Ceramic 300-mil DIPs (J, N)

description


The 'BCT623 bus transceiver is designed for asynchronous communication between data buses. The control function implementation allows for maximum flexibility in timing. The 'BCT623 provides true data at its outputs.

This device allows data transmission from the A bus to the B bus or from the B bus to the A bus depending upon the <u>logic</u> levels at the output-enable (OEAB and OEBA) inputs.


The output-enable inputs can be used to disable the device so that the buses are effectively isolated. The dual-enable configuration gives the transceivers the capability of storing data by simultaneously enabling OEAB and OEBA. Each output reinforces its input in this configuration. When both OEAB and OEBA are enabled and all other data sources to the two sets of bus lines are at high impedance, both sets of bus lines (16 in all) will remain at their last states.

The SN54BCT623 is characterized for operation over the full military temperature range of -55° C to 125°C. The SN74BCT623 is characterized for operation from 0°C to 70°C.

SN54BCT623 . . . J OR W PACKAGE SN74BCT623 . . . DW OR N PACKAGE (TOP VIEW)




SN54BCT623 . . . FK PACKAGE (TOP VIEW)




FUNCTION TABLE

INP	UTS	ODEDATION
OEBA	OEAB	OPERATION
L	L	B data to A bus
L	Н	B data to A bus, A data to B bus
Н	L	Isolation
Н	Н	A data to B bus

logic symbol[†]



logic diagram (positive logic)



absolute maximum ratings over operating free-air temperature range (unless otherwise noted)‡

Supply voltage range, V _{CC}	– 0.5 V to 7 V
Input voltage range: Control inputs (see Note 1)	– 0.5 V to 7 V
I/O ports (see Note 1)	– 0.5 V to 5.5 V
Voltage range applied to any output in the disabled or power-off state, VO	– 0.5 V to 5.5 V
Voltage range applied to any output in the high state, V _O	– 0.5 V to V _{CC}
Input clamp current, I _{IK}	–30 mA
Current into any output in the low state: SN54BCT623	96 mA
SN74BCT623	128 mA
Operating free-air temperature range: SN54BCT623	– 55°C to 125°C
SN74BCT623	0°C to 70°C
Storage temperature range	– 65°C to 150°C

[‡] Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

recommended operating conditions

			SN	SN54BCT623			SN74BCT623			
			MIN	NOM	MAX	MIN	NOM	MAX	UNIT	
VCC	Supply voltage		4.5	5	5.5	4.5	5	5.5	V	
VIH	High-level input voltage		2			2			V	
VIL	Low-level input voltage				8.0			0.8	V	
liK	Input clamp current				-18			-18	mA	
		A port			-3			-3		
ЮН	High-level output current	B port		-12				-15	mA	
		A port			20			24		
loL	Low-level output current	B port			48			64	mA	
TA	Operating free-air temperature		-55		125	0		70	°C	



[†] This symbol is in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12.

NOTE 1: The input and output voltage ratings may be exceeded if the input and output current ratings are observed.

SCBS020A - SEPTEMBER 1988 - REVISED NOVEMBER 1993

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

DADAMETED				SN	I54BCT6	23	SN	74BCT6	23	
	PARAMETER	TES	T CONDITIONS	MIN	TYP	MAX	MIN	TYP [†]	MAX	UNIT
VIK		V _{CC} = 4.5 V,	I _I = -18 mA			-1.2			-1.2	V
	Amount	V 45V	I _{OH} = -1 mA	2.5	3.4		2.5	3.4		
	A port	$V_{CC} = 4.5 \text{ V}$	IOH = -3 mA	2.4	3.3		2.4	3.3		
۷он			$I_{OH} = -3 \text{ mA}$	2.4	3.3		2.4	3.3		V
	B port	V _{CC} = 4.5 V	$I_{OH} = -12 \text{ mA}$	2	3.2					
			$I_{OH} = -15 \text{ mA}$				2	3.1		
	A mant	\/ 45\/	$I_{OL} = 20 \text{ mA}$		0.3	0.5				
V/	A port	V _{CC} = 4.5 V	$I_{OL} = 24 \text{ mA}$					0.35	0.5	V
V_{OL}	Roort	\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\	$I_{OL} = 48 \text{ mA}$		0.38	0.55				V
	B port $V_{CC} = 4.5 \text{ V}$		$I_{OL} = 64 \text{ mA}$					0.42	0.55	
1.		\/aa	V.			1			1	mA
l _l		V _I = 5.5 V			0.1			0.1	mA	
ı†	A or B port	\/aa	\/. 27\/			70			70	^
I _{IH} ‡	OEAB or OEBA	$V_{CC} = 5.5 \text{ V},$	V _I = 2.7 V			20			20	μΑ
I _{IL} ‡	A or B port	\/aa	\/. 0 E \/			-0.65			-0.65	mA
IIL+	OEAB or OEBA	$V_{CC} = 5.5 \text{ V},$	V _I = 0.5 V			-0.6			-0.6	MA
1 8	A port	\/	V- 0	-60		-150	-60		-150	mA
los§	B port	$V_{CC} = 5.5 \text{ V},$	V _O = 0	-100		-225	-100		-225	mA
ICCL	A to B	V _{CC} = 5.5 V			58	92		58	92	mA
ICCH	A to B	V _{CC} = 5.5 V			33	53		33	53	mA
ICCZ		V _{CC} = 5.5 V			6	11		6	11	mA
Ci	OEAB or OEBA	$V_{CC} = 5 V$,	$V_{ } = 2.5 \text{ V or } 0.5 \text{ V}$		5			5		pF
C.	A to B	V _{CC} = 5 V,	V _O = 2.5 V or 0.5 V		9			9		pF
Cio	B to A	\(\frac{1}{2}\)\(\frac{1}\)\(\frac{1}{2}\)\(\frac{1}{2}\)\(\frac{1}{2}\)\(\frac{1}{2}\)\(\frac{1}\)\(\frac{1}{2}\)\(\frac{1}\)\(\frac{1}\)\(\frac{1}{2}\)\(\frac{1}{2}\)\(\frac{1}{2}\)\(\frac{1}{2}\)\(\frac{1}{2}\)\(\	VO = 2.5 V 01 0.5 V		12			12		þΓ

[†] All typical values are at V_{CC} = 5 V, T_A = 25°C. ‡ For I/O ports, the parameters I_{IH} and I_{IL} include the off-state output current. § Not more than one output should be tested at a time, and the duration of the test should not exceed one second.

SN54BCT623, SN74BCT623 OCTAL BUS TRANSCEIVERS WITH 3-STATE OUTPUTS

SCBS020A - SEPTEMBER 1988 - REVISED NOVEMBER 1993

switching characteristics (see Note 2)

PARAMETER	FROM TO (OUTPUT)		$V_{CC} = 5 \text{ V},$ $C_L = 50 \text{ pF},$ $R1 = 500 \Omega,$ $R2 = 500 \Omega,$ $T_A = 25^{\circ}C$			V_{CC} = 4.5 V to 5.5 V, C_L = 50 pF, R1 = 500 Ω, R2 = 500 Ω, T_A = MIN to MAX †				UNIT	
			′1	′BCT623			CT623	SN74B			
			MIN	TYP	MAX	MIN	MAX	MIN	MAX		
t _{PLH}	^	ь	0.5	3.1	4.7	0.5	5.3	0.5	5.2		
t _{PHL}	А	В	1.7	4.9	6.9	1.7	7.6	1.7	7.4	ns	
t _{PLH}		^	0.9	4.1	5.9	0.9	6.8	0.9	6.7	ns	
t _{PHL}	В	Α	1.8	5.3	7.6	1.8	8.3	1.8	8		
^t PZH	OEBA	Δ.	3.1	6.8	9.1	3.1	10.7	3.1	10.6		
t _{PZL}	OEBA	А	3.3	7.2	9.6	3.3	11.3	3.3	10.7	ns	
t _{PHZ}	OEBA		1.9	6.1	8.3	1.9	10.6	1.9	9.8		
tPLZ	OEBA	А	1.1	4.6	7	1.1	8.1	1.1	7.8	ns	
^t PZH	OFAR	D	2	5	6.8	2	7.8	2	7.6	20	
tpZL	OEAB	В	2.7	6.2	8	2.7	9.3	2.7	8.9	ns	
t _{PHZ}	OEAB	В	1.1	4.6	6.5	1.1	8	1.1	7.7		
t _{PLZ}	UEAD	D	0.3	3.2	6.3	0.3	7.2	0.3	7.1	ns	

[†] For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions. NOTE 2: Load circuits and voltage waveforms are shown in Section 1.







11-Jul-2015

PACKAGING INFORMATION

Orde	erable Device	Status	Package Type		Pins		Eco Plan	Lead/Ball Finish	MSL Peak Temp	Op Temp (°C)	Device Marking	Samples
		(1)		Drawing		Qty	(2)	(6)	(3)		(4/5)	
5962-	-9094001M2A	LIFEBUY	LCCC	FK	20	1	TBD	POST-PLATE	N / A for Pkg Type	-55 to 125	5962- 9094001M2A SNJ54BCT 623FK	
5962-	-9094001MRA	ACTIVE	CDIP	J	20	1	TBD	A42	N / A for Pkg Type	-55 to 125	5962-9094001MR A SNJ54BCT623J	Samples
5962-	-9094001MSA	LIFEBUY	CFP	W	20	1	TBD	A42	N / A for Pkg Type	-55 to 125	5962-9094001MS A SNJ54BCT623W	
SN7	74BCT623N	ACTIVE	PDIP	N	20	20	Pb-Free (RoHS)	CU NIPDAU	N / A for Pkg Type	0 to 70	SN74BCT623N	Samples
SN74	4BCT623NSR	ACTIVE	SO	NS	20	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM	0 to 70	BCT623	Samples
SNJ5	54BCT623FK	LIFEBUY	LCCC	FK	20	1	TBD	POST-PLATE	N / A for Pkg Type	-55 to 125	5962- 9094001M2A SNJ54BCT 623FK	
SNJ	J54BCT623J	ACTIVE	CDIP	J	20	1	TBD	A42	N / A for Pkg Type	-55 to 125	5962-9094001MR A SNJ54BCT623J	Samples
SNJ	54BCT623W	LIFEBUY	CFP	W	20	1	TBD	A42	N / A for Pkg Type	-55 to 125	5962-9094001MS A SNJ54BCT623W	

⁽¹⁾ The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBSOLETE: TI has discontinued the production of the device.

TBD: The Pb-Free/Green conversion plan has not been defined.

Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

⁽²⁾ Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.





11-Jul-2015

Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above. **Green (RoHS & no Sb/Br):** TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

- (3) MSL, Peak Temp. The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.
- (4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.
- (5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.
- (6) Lead/Ball Finish Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead/Ball Finish values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

OTHER QUALIFIED VERSIONS OF SN54BCT623, SN74BCT623:

Catalog: SN74BCT623

Military: SN54BCT623

NOTE: Qualified Version Definitions:

- Catalog TI's standard catalog product
- Military QML certified for Military and Defense Applications

PACKAGE MATERIALS INFORMATION

www.ti.com 24-Apr-2015


TAPE AND REEL INFORMATION





	Dimension designed to accommodate the component width
	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing			Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
SN74BCT623NSR	SO	NS	20	2000	330.0	24.4	9.0	13.0	2.4	4.0	24.0	Q1

www.ti.com 24-Apr-2015



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
SN74BCT623NSR	SO	NS	20	2000	367.0	367.0	45.0

14 LEADS SHOWN



- A. All linear dimensions are in inches (millimeters).
- B. This drawing is subject to change without notice.
- C. This package is hermetically sealed with a ceramic lid using glass frit.
- D. Index point is provided on cap for terminal identification only on press ceramic glass frit seal only.
- E. Falls within MIL STD 1835 GDIP1-T14, GDIP1-T16, GDIP1-T18 and GDIP1-T20.

W (R-GDFP-F20)

CERAMIC DUAL FLATPACK



- A. All linear dimensions are in inches (millimeters).
- This drawing is subject to change without notice.
- C. This package can be hermetically sealed with a ceramic lid using glass frit.

 D. Index point is provided on cap for terminal identification only.

 E. Falls within Mil—Std 1835 GDFP2—F20



FK (S-CQCC-N**)

LEADLESS CERAMIC CHIP CARRIER

28 TERMINAL SHOWN



- A. All linear dimensions are in inches (millimeters).
- B. This drawing is subject to change without notice.
- C. This package can be hermetically sealed with a metal lid.
- D. Falls within JEDEC MS-004



N (R-PDIP-T**)

PLASTIC DUAL-IN-LINE PACKAGE

16 PINS SHOWN



- A. All linear dimensions are in inches (millimeters).
- B. This drawing is subject to change without notice.
- Falls within JEDEC MS-001, except 18 and 20 pin minimum body length (Dim A).
- The 20 pin end lead shoulder width is a vendor option, either half or full width.



MECHANICAL DATA

NS (R-PDSO-G**)

14-PINS SHOWN

PLASTIC SMALL-OUTLINE PACKAGE



- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- C. Body dimensions do not include mold flash or protrusion, not to exceed 0,15.



IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have *not* been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products Applications

Audio www.ti.com/audio Automotive and Transportation www.ti.com/automotive **Amplifiers** amplifier.ti.com Communications and Telecom www.ti.com/communications **Data Converters** dataconverter.ti.com Computers and Peripherals www.ti.com/computers **DLP® Products** www.dlp.com Consumer Electronics www.ti.com/consumer-apps DSP dsp.ti.com **Energy and Lighting** www.ti.com/energy Clocks and Timers www.ti.com/clocks Industrial www.ti.com/industrial Interface interface.ti.com Medical www.ti.com/medical Logic Security www.ti.com/security logic.ti.com

Power Mgmt power.ti.com Space, Avionics and Defense www.ti.com/space-avionics-defense

Microcontrollers microcontroller.ti.com Video and Imaging www.ti.com/video

RFID www.ti-rfid.com

OMAP Applications Processors www.ti.com/omap TI E2E Community e2e.ti.com

Wireless Connectivity www.ti.com/wirelessconnectivity