National Semiconductor is now part of Texas Instruments.

Search http://www.ti.com/ for the latest technical information and details on our current products and services.



LM161/LM361

High Speed Differential Comparators

General Description

The LM161/LM361 is a very high speed differential input, complementary TTL output voltage comparator with improved characteristics over the SE529/NE529 for which it is a pin-for-pin replacement. The device has been optimized for greater speed performance and lower input offset voltage. Typically delay varies only 3 ns for over-drive variations of 5 mV to 500 mV. It may be operated from op amp supplies (±15V).


Complementary outputs having maximum skew are provided. Applications involve high speed analog to digital converters and zero-crossing detectors in disk file systems.

Features

- Independent strobes
- Guaranteed high speed: 20 ns max
- Tight delay matching on both outputs
- Complementary TTL outputs
- Operates from op amp supplies: ±15V
- Low speed variation with overdrive variation
- Low input offset voltage
- Versatile supply voltage range


Connection Diagrams

Dual-In-Line Package




Top View
Order Number LM361M, LM361MX or LM361N
See NS Package Number M14A or N14A

Metal Can Package



Order Number LM161H/883 or LM361H See NS Package Number H10C

Logic Diagram



*Output is low when current is drawn from strobe pin.

Absolute Maximum Ratings (Note 1)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/ Distributors for availability and specifications.

Positive Supply Voltage, V+	+16V
Negative Supply Voltage, V-	-16V
Gate Supply Voltage, V _{CC}	+7V
Output Voltage	+7V
Differential Input Voltage	±5V
Input Common Mode Voltage	±6V
Power Dissipation	600 mW
Storage Temperature Range	-65°C to +150°C
Operating Temperature Range	T_{MIN} T_{MAX}
LM161	-55°C to +125°C
	-25°C to +85°C
LM361	0°C to +70°C
Lead Temp. (Soldering, 10 seconds)	260°C
For Any Device Lead Below V-	0.3V

	Min	Тур	Max		
LM361	5V		15V		
Supply Voltage V ⁻					
LM161	-6V		-15V		
LM361	-6V		-15V		
Supply Voltage V_{CC}					
LM161	4.5V	5V	5.5V		
LM361	4.75V	5V	5.25V		
ESD Tolerance (Note 5)			1600V		
Soldering Information					
Dual-In-Line Package					
Soldering (10 secon	ds)		260°C		
Small Outline Package					
Vapor Phase (60 se	conds)		215°C		
Infrared (15 seconds	s)		220°C		

See AN-450 "Surface Mounting Methods and Their Effect on Product Reliability" for other methods of soldering surface mount devices.

Operating Conditions

	IVIII	тур	IVIAX
Supply Voltage V ⁺			
LM161	5V		15V

Electrical Characteristics

(V⁺ = +10V, V_{CC} = +5V, V^- = -10V, $T_{MIN} \le T_A \le T_{MAX}$, unless noted)

		Limits						
Parameter	Conditions	LM161		LM361			Units	
		Min	Тур	Max	Min	Тур	Max	
Input Offset Voltage			1	3		1	5	mV
Input Bias Current	T _A =25°C		5			10		μΑ
				20			30	μΑ
Input Offset Current	T _A =25°C		2			2		μΑ
				3			5	μΑ
Voltage Gain	T _A =25°C		3			3		V/mV
Input Resistance	T _A =25°C, f=1 kHz		20			20		kΩ
Logical "1" Output Voltage	V _{CC} =4.75V,	2.4	3.3		2.4	3.3		V
	I _{SOURCE} =-0.5 mA							
Logical "0" Output Voltage	V _{CC} =4.75V,			0.4			0.4	V
	I _{SINK} =6.4 mA							
Strobe Input "1" Current	V _{CC} =5.25V,			200			200	μΑ
(Output Enabled)	V _{STROBE} =2.4V							
Strobe Input "0" Current	V _{CC} =5.25V,			-1.6			-1.6	mA
(Output Disabled)	V _{STROBE} =0.4V							
Strobe Input "0" Voltage	V _{CC} =4.75V			0.8			0.8	V
Strobe Input "1" Voltage	V _{CC} =4.75V	2			2			V
Output Short Circuit Current	V _{CC} =5.25V, V _{OUT} =0V	-18		-55	-18		-55	mA
	V+=10V, V-=-10V,							
Supply Current I+	V _{CC} =5.25V,			4.5				mA
	–55°C≤T _A ≤125°C							

www.national.com

Electrical Characteristics (Continued)

 $(V^{+} = +10V, V_{CC} = +5V, V^{-} = -10V, T_{MIN} \le T_{A} \le T_{MAX}, unless noted)$

		Limits						
Parameter	Conditions	LM161		LM361			Units	
		Min	Тур	Max	Min	Тур	Max	
	V ⁺ =10V, V ⁻ =-10V,							
Supply Current I ⁺	V _{CC} =5.25V, 0°C≤T _A ≤70°C						5	mA
Supply Current I ⁻	V ⁺ =10V, V ⁻ =−10V, V _{CC} =5.25V, −55°C≤T _A ≤125°C			10				mA
Supply Current I⁻	V ⁺ =10V, V ⁻ =-10V,V _{CC} =5.25V, 0°C≤T _A ≤70°C						10	mA
Supply Current I _{CC}	V ⁺ =10V, V ⁻ =-10V, V _{CC} =5.25V, -55°C≤T _A ≤125°C			18				mA
Supply Current I _{CC}	V+=10V, V ⁻ =-10V, V _{CC} =5.25V, 0°C≤T _A ≤70°C						20	mA
Transient Response	V _{IN} = 50 mV overdrive (Note 3)							
Propagation Delay Time (tpd(0))	T _A =25°C		14	20		14	20	ns
Propagation Delay Time (t _{pd(1)})	T _A =25°C		14	20		14	20	ns
Delay Between Output A and B	T _A =25°C		2	5		2	5	ns
Strobe Delay Time (t _{pd(0)})	T _A =25°C		8			8		ns
Strobe Delay Time (tpd(1))	T _A =25°C		8			8		ns

Note 1: The device may be damaged by use beyond the maximum ratings.

Note 2: Typical thermal impedances are as follows:

	H Package	J Package	N Package
θ_{jA}	165°C/W (Still Air) 67°C/W (400 LF/Min Air Flow)	112°C/W	105°C/W
θ :C	25°C/W		


00570817

Note 3: Measurements using AC Test circuit, Fanout = 1. The devices are faster at low supply voltages.

Note 4: Refer to RETS161X for LM161H and LM161J military specifications.


Note 5: Human body model, 1.5 k Ω in series with 100 pF.

Typical Performance Characteristics



00570808


Input Currents vs Ambient Temperature



00570809


Input Characteristics

AMBIENT TEMPERATURE ("C)




00570810

Supply Current vs Ambient Temperature




00570811

Supply Current vs Supply Voltage




Propagation Delay vs Ambient Temperature




00570813


Typical Performance Characteristics (Continued)


Delay of Output 1 With Respect to Output 2 vs **Ambient Temperature**






00570815






Propagation Delay vs Supply Voltage 80 70 60



00570807

AC Test Circuit



 $V_{IN} = \pm 50 \text{ mV}$

FANOUT = 1

FANOUT = 4

 $V^{-} = -10V$

C=15 pF

C = 30 pF

 $V^{+} = +10V$

R = 2.4k


 $R = 680\Omega$

 $V_{CC} = 5.25V$


Schematic Diagram LM161 • STROBE1 • V_{CC} ₹R10 100 R9 **₹**R8 **≹**R7 1k D12 Q15 **₹**R3 9k D10 O NON-INVERTING OUTPUT1 R11 235 R12 800 O GND R1 1450 **₹** O STROBE2 R15 R15 1.4k ₹R16 ₹R2 1450 ≹R13 1k Q5 Q20 R19 5k Q6 Q19 R5 1.3k **₹**R6 1.3k **D**9 O INVERTING OUTPUT2 D5 **Z** R17 **₹** D6 Q2 +INPUT1 O-Q10 Q7 Q22 R18 800 -INPUT2 O **₹**R20 3.2k D8 R21 387 Q12 Q13 400 00570801


R10, R16: 85 R11, R17: 205

Physical Dimensions inches (millimeters) unless otherwise noted




Metal Can Package (H) Order Number LM161H/883, or LM361H **NS Package Number H10C**







Order Number LM361M or LM361MX **NS Package Number M14A**


Physical Dimensions inches (millimeters) unless otherwise noted (Continued)





OPTION 02





Molded Dual-In-Line Package (N) Order Number LM361N NS Package Number N14A

National does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry and specifications.

For the most current product information visit us at www.national.com.

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT AND GENERAL COUNSEL OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
- 2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

BANNED SUBSTANCE COMPLIANCE

National Semiconductor certifies that the products and packing materials meet the provisions of the Customer Products Stewardship Specification (CSP-9-111C2) and the Banned Substances and Materials of Interest Specification (CSP-9-111S2) and contain no "Banned Substances" as defined in CSP-9-111S2.



National Semiconductor Americas Customer Support Center

Email: new.feedback@nsc.com Tel: 1-800-272-9959

National Semiconductor Europe Customer Support Center Fax: +49 (0) 180-530 85 86

Email: europe.support@nsc.com
Deutsch Tel: +49 (0) 69 9508 6208
English Tel: +44 (0) 870 24 0 2171 Français Tel: +33 (0) 1 41 91 8790

National Semiconductor Asia Pacific Customer Support Center Email: ap.support@nsc.com **National Semiconductor** Japan Customer Support Center Fax: 81-3-5639-7507 Email: jpn.feedback@nsc.com Tel: 81-3-5639-7560